

Pocket Multimeter Hioki 3244-60

Hioki 3244-60 Pocket Multimeter is a compact and versatile measurement tool designed for use in a wide range of applications. It features a range of measurement functions and is suitable for use in both professional and hobbyist environments.

Applications: Electrical maintenance and troubleshooting, HVAC system maintenance, Automotive repair, Laboratory research, Electronics Manufacturing, Renewable energy systems.

Hioki 3244-60 Pocket Multimeter is a compact and portable device designed to provide accurate readings of various electrical parameters. It comes with a range of features that make it a versatile tool for professionals and hobbyists alike.

Features of Hioki Pocket Multimeter

- Card-size tester that's easy to use in the field
- Included hard case for tidy storage
- Tester with a simple, easy-to-read display



Manufacturer	Hioki
Model No	3244-60
DC Voltage	419.9 mV to 500 V, 5 ranges,
	Basic accuracy: ±0.7 % rdg. ±4 dgt.
AC Voltage	4.199 V to 500 V, 4 ranges, Basic accuracy 50 - 500 Hz : ±2.3 % rdg. ±8 dgt. (Average rectified)
Resistance	419.9 Ω to 41.99 M Ω , 6 ranges,
	Basic accuracy: ±2.0 % rdg. ±4 dgt.
Continuity buzzer	Detection level 50 Ω ±40 Ω ,
	Diode check: Not available
Auto power save	Available (cancel selectable)
Display	Digital LCD, max. 4199 digits
Sampling Rate	2.5 times/sec
Power Supply	Coin type lithium battery (CR2032) ×1,
	Continuous use: 150 hours
Supply Scope	Instruction manual ×1, Carrying case ×1, Coin type lithium battery (CR2032) ×1 (for trial purposes only), Sleeves (Red/ Black each 1)
Dimension	55 mm (2.17 in) W × 109 mm (4.29 in) H × 9.5 mm (0.37 in) D
Weight	60 Grams

Temp | Humidity | Pressure | Differential Pressure | Vacuum | Gases | Particle | Air Flow Moisture | Dissolved Oxygen | Radiation | Air Quality | Light / Lux | Distance | Vibration

Instrukart Holdings

Ph: +91 (40)40262020 | Mob: +91 88865 50506; Email: info@instrukart.com | www.instrukart.com

Head Office: #18,Street-1A, Czech Colony, Sanath Nagar, Hyderabad -500018, INDIA.



