

Phase Sequence Indicator

Hioki PD-3129-10

Hioki PD-3129-10 Phase Sequence Indicator is a highly reliable and easy-to-use tool for detecting the phase sequence of three-phase power lines. This Phase Detector is designed with accuracy and safety in mind and one of the key features of the Hioki PD-3129-10 is its ability to detect the phase sequence of both AC and DC power sources.

Applications: : Industrial, commercial, and residential settings.

Hioki PD-3129-10 Phase Sequence Indicator is designed to be easy to use and is suitable for both novice and experienced users. It features a compact and lightweight design that makes it easy to carry and store. This Phase Indicator is a non-contact phase rotation meter that detects the phase of electrical current flow within insulated wires without using metallic contact voltage clips.

Feature

- Easy-to-understand detection of normal phase with lit arrow
- Safe, no-metal-contact design
- Magnetic back for maximum work efficiency



Manufacturer	Hioki
Model No	PD-3129-10
Measuring Parameters	Phase detection
Voltage measurement	Static induction
Voltage Range	70 to 1000 V AC (50/60 Hz)
Frequency	45 Hz to 66 Hz
Object to be connected	7mm (0.28 in) to 40 mm (1.57 in) of insulated wiring
Indication	Phase detection : Positive ; 4 LEDs lit in clockwise order and the buzzer sounds intermittently, green arrow lights up Negative ; 4 LEDs lit in counterclockwise order and the buzzer sounds continuously
Auto Power Off	Auto shut off if no activity is detected after power is turned ON for 15 minutes
Power Supply	R6P (AA) manganese battery ×2, Continuous use: 70 hr
Supply Scope	Carrying case ×1, Strap ×1, Spiral tube ×1, Instruction manual ×1, R6P (AA) manganese battery ×2
Dimensions	70 mm (2.76 in)W × 75 mm (2.95 in)H × 30 mm (1.18 in)D
Weight	240 g

Temp | Humidity | Pressure | Differential Pressure | Vacuum | Gases | Particle | Air Flow
Moisture | Dissolved Oxygen | Radiation | Air Quality | Light / Lux | Distance | Vibration

Instrukart Holdings

Ph : +91 (40)40262020 | Mob : +91 88865 50506;

Email : info@instrukart.com | www.instrukart.com

Head Office: #18,Street-1A, Czech Colony, Sanath Nagar, Hyderabad -500018, INDIA.

 <https://youtube.com/instrukartholdings>

